

56 Sparta Avenue • Newton, New Jersey 07860
 (973) 300-3000 Sales • (973) 300-3600 Fax
 www.thorlabs.com



KT110/M - September 9, 2021

Item # KT110/M was discontinued on September 9, 2021. For informational purposes, this is a copy of the website content at that time and is valid only for the stated product.

FIBER COUPLING AND SPATIAL FILTER SYSTEMS

- ▶ Free Space Fiber Launch System with Submicron XY Translator
- ▶ Spatial Filter System Produces "Clean" Gaussian Beams



KT311
Spatial Filter System



KT120
Free-Space
Fiber Coupler

OVERVIEW

Features

- KT120 or KT110/M Fiber Coupler Accepts FC or SMA Fiber Cables
- High-Precision Differential Adjusters Included with KT120 and KT110/M Provide Submicron Translation
- KT311(M) Spatial Filter Directly Compatible with Ø9 mm Aspheric Lens Housings
- Easy-to-Follow Instructions and Alignment Tools

Recommended Focusing Optics ^a	
Item #	Description
C230TMD-A	350 - 700 nm, f = 4.51 mm, NA = 0.55 Aspheric Lens
C230TMD-B	600 - 1050 nm, f = 4.51 mm, NA = 0.55 Aspheric Lens
C230TMD-C	1050 - 1700 nm, f = 4.51 mm, NA = 0.55 Aspheric Lens

- Focusing optics are not included with these systems.

Fiber Launch Systems

Thorlabs' KT120 and KT110/M fiber launch systems couple free-space laser beams into fiber optic cables. These systems, which can be used with single or multimode fiber, are equipped with high-precision differential adjusters capable of submicron translation.

These fiber launch systems only include optomechanical components (see the *Components* tab for a complete list of components). The table to the upper right lists the recommended optics for focusing collimated light into an output fiber connected to the KT120 or KT110/M system. Note that to reach the best coupling performance into a multimode fiber, the numerical aperture of the lens should match that of the fiber. Similarly, for optimized coupling into a single mode fiber the spot size of the focused beam must be less than the mode-field diameter of the fiber.

Spatial Filter Systems

Many applications, such as holography, require a beam with uniform intensity. The KT311(M) spatial filter is ideal for producing a clean, spatially uniform, Gaussian beam. The input of this system consists of a Z-axis translator, which can house a diffraction-limited aspheric lens. This aspheric lens focuses the beam through a pinhole, which can be mounted in the XY translator. The output consists of a Ø1" cage mount, which holds and centers a collimating optic.

This filter system only includes optomechanical components (see the *Components* tab for a complete list of components). The aspheric lens, collimating optics, and pinhole must be purchased separately. Please refer to the *Tutorial* tab for more information on choosing the appropriate optics and pinhole for your application.

KT120	KT110/M	Description	Qty.
CP33	CP02/M ^a	SM1-Threaded 30 mm Cage Plate	1
CPA1		30 mm Cage System Alignment Plate	1
E09RMS		Extended RMS to M9 x 0.5 Adapter	1
ER2		Cage Assembly Rod, 2" Long	4
ER3		Cage Assembly Rod, 3" Long	4
MA2	MA2/M	Ø1.5" Post Mounting Adapter	1
P1.5	P30/M	Ø1.5" Mounting Post	1
PB1		Mounting Post Base	1
SM1A3		Adapter with External SM1 Threads and Internal RMS Threads	1
SM1D12		SM1 Lever-Actuated Iris Diaphragm	1
SM1FC		FC/PC Fiber Adapter Plate	1
SM1RR		SM1 Retaining Ring	3
SM1ZA	SM1Z ^b	Z-Axis Translation Mount	1
SPW301		Spanner Wrench for a M9 x 0.5 Optics Housing	1
SPW801		Adjustable Spanner Wrench	1
ST1XY-D	ST1XY-D/M	XY Translator with Differential Drives	1
SM1SMA		SMA Fiber Adapter Plate	1
-		5/64" (KT120 Only) or 0.05" (KT110/M Only) Hex Key ^c	1

- a. This previous-generation item is not available for individual purchase. If a replacement is needed, the CP33/M can be used for metric kits.
- b. This previous-generation item is not available for individual purchase. If a replacement is needed, the SM1ZA can be used for both imperial and metric kits.
- c. Additional hex keys can be purchased separately in packs of 10 (Item # 564HK for 5/64" hex or Item # HK050 for 0.050" hex).



KT311	KT311/M	Description	Qty.
CPA1		30 mm Cage System Alignment Plate	1
KT311	KT311/M	Description	Qty.
E09RMS		Extended RMS to M9 x 0.5 Adapter	1
ER2		Cage Assembly Rod, 2" Long	8
MA2	MA2/M	Ø1.5" Post Mounting Adapter	1
P2	P50/M	Ø1.5" Mounting Post	1
PB1		Mounting Post Base	1
SM1L03		SM1 Lens Tube, 0.3" Thread Depth	1
SM1A3		Adapter with External SM1 Threads and Internal RMS Threads	1
SM1RR		SM1 Retaining Ring	3
SM1ZA		Z-Axis Translation Mount	1
SPT1C	SPT1C/M	Coarse ±1 mm XY Slip Plate Positioner	1
SPW301		Spanner Wrench for a M9 x 0.5 Optics Housing	1
SPW801		Adjustable Spanner Wrench	1
ST1XY-A	ST1XY-A/M	XY Translator with 100 TPI Drives	1
-		5/64" (2.0 mm) Hex Key ^a	1

- a. Additional hex keys can be purchased separately in packs of 10 (Item # 564HK).



Principles of Spatial Filters

For many applications, such as holography, spatial intensity variations in the laser beam are unacceptable. Our KT311(/M) spatial filter system is ideal for producing clean Gaussian beams.




Figure 1: Spatial Filter System

The input Gaussian beam has spatially varying intensity "noise". When a beam is focused by an aspheric lens, the input beam is transformed into a central Gaussian spot (on the optical axis) and side fringes, which represent the unwanted "noise" (see Figure 2 below). The radial position of the side fringes is proportional to the spatial frequency of the "noise".




Figure 2

By centering a pinhole on a central Gaussian spot, the "clean" portion of the beam can pass while the "noise" fringes are blocked (see Figure 3 below).




Figure 3

The diffraction-limited spot size at the 99% contour is given by:

$$D = \frac{\lambda f}{r}$$

where λ = wavelength, f =focal length and r = input beam radius at the $1/e^2$ point.

Choosing the Correct Optics and Pinhole for Your Spatial Filter System

The correct optics and pinhole for your application depend on the input wavelength, source beam diameter, and desired exit beam diameter.

For example, suppose that you are using a 650 nm diode laser source that has a diameter ($1/e^2$) of 1.2 mm and want your beam exiting the spatial filter system to be about 4.4 mm in diameter. Based on these parameters, the C560TME-B mounted aspheric lens would be an appropriate choice for the input side of spatial filter system because it is designed for use at 650 nm, and its clear aperture measures 5.1 mm, which is large enough to accommodate the entire diameter of the laser source.

The equation for diffraction limited spot size at the 99% contour is given above, and for this example, $\lambda = (650 \times 10^{-9} \text{ m})$, $f = 13.86 \text{ mm}$ for the C560TM-B, and $r = 0.6 \text{ mm}$. Substitution yields

$$D = \frac{(650 \times 10^{-9} \text{ m})(13.86 \text{ mm})}{0.6 \text{ mm}} \approx 15 \mu\text{m}$$

Diffraction-Limited Spot Size (650 nm source, Ø1.2 mm beam)

The pinhole should be chosen so that it is approximately 30% larger than D . If the pinhole is too small, the beam will be clipped, but if it is too large, more than the TEM_{00} mode will get through the pinhole. Therefore, for this example, the pinhole should ideally be 19.5 microns. Hence, we would recommend the mounted pinhole P20K, which has a pinhole size of 20 μm . Parameters that can be changed to alter the beam waist diameter, and thus the pinhole size required, include changing the input beam diameter and focal length of focusing lens. Decreasing the input beam diameter will increase the beam waist diameter. Using a longer focal length focusing lens will also increase the beam waist diameter.

Finally, we need to choose the optic on the output side of the spatial filter so that the collimated beam's diameter is the desired 4.4 mm. To determine the correct focal length for the lens, consider the following diagram in Figure 4, which is not drawn to scale. From the triangle on the left-hand side, the angle is determined to be approximately 2.48° . Using this same angle for the triangle on the right-hand side, the focal length for the plano-convex lens should be approximately 50 mm.




Figure 4: Beam Expansion Example

For this focal length, we recommend the LA1131-B plano-convex lens [with $f = 50 \text{ mm}$ at the design wavelength ($\lambda = 633 \text{ nm}$), this is still a good approximation for f at the source wavelength ($\lambda = 650 \text{ nm}$)].

Note: The beam expansion equals the focal length of the output side divided by the focal length of the input side.

For optimal performance, a large-diameter aspheric lens can be used in place of a plano-convex lens if the necessary focal length on the output side is 20 mm (see AL2520-A, AL2520-B, AL2520-C). These lenses are 25 mm in diameter and can be held in place using the supplied SM1RR Retaining Ring.

Comparison of Circularization Techniques for Elliptical Beams


Lab Facts

[Click for Full Lab Facts Summary](#)

Edge-emitting laser diodes emit elliptical beams as a consequence of the rectangular cross sections of their emission apertures. The component of the beam corresponding to the narrower dimension of the aperture has a greater divergence angle than the orthogonal beam component. As one component diverges more rapidly than the other, the beam shape is elliptical rather than circular.

Elliptical beam shapes can be undesirable, as the spot size of the focused beam is larger than if the beam were circular, and as larger spot sizes have lower irradiances (power per area). Techniques for circularizing an elliptical beam include those based on a pair of cylindrical lenses, an anamorphic prism pair, or a spatial filter. This work investigated all three approaches. The characteristics of the circularized beams were evaluated by performing M^2 measurements, wavefront measurements, and measuring the transmitted power.

While it was demonstrated that each circularization technique improves the circularity of the elliptical input beam, each technique was shown to provide a different balance of circularization, beam quality, and transmitted power. The results of this work, which are documented in this Lab Fact, indicate that an application's specific requirements will determine which is the best circularization technique to choose.



[Click to Enlarge](#)


Figure 1: The beam circularization systems were placed in the area of the experimental setup highlighted by the yellow rectangle.



[Click to Enlarge](#)
Figure 2: Cylindrical Lens Pair System



[Click to Enlarge](#)
Figure 3: Anamorphic Prism Pair System



[Click to Enlarge](#)
Figure 4: Spatial Filter System

Experimental Design and Setup

The experimental setup is shown in Figure 1. The elliptically-shaped, collimated beam of a temperature-stabilized 670 nm laser diode was input to each of our circularization systems shown in Figures 2 through 4. Collimation results in a low-divergence beam, but it does not affect the beam shape. Each system was based on one of the following:

- LJ1874L2-A and LJ1638L1-A Plano-Convex Convex Cylindrical Lenses (Figure 2)
- PS873-A Unmounted Anamorphic Prism Pair (Figure 3)
- Previous Generation KT310 Spatial Filter System with P5S $\varnothing 5 \mu\text{m}$ Pinhole (Figure 4)

The beam circularization systems, shown to the right, were placed, one at a time, in the vacant spot in the setup highlighted by the yellow rectangle. With this arrangement, it was possible to use the same experimental conditions when evaluating each circularization technique, which allowed the performance of each to be directly compared with the others. This experimental constraint required the use of fixturing that was not optimally compact, as well as the use of an unmounted anamorphic prism pair, instead of a more convenient mounted and pre-aligned anamorphic prism pair.

The characteristics of the beams output by the different circularization systems were evaluated by making measurements using a power meter, a wavefront sensor, and an M^2 system. In the image of the experimental setup, all of these systems are shown on the right side of the table for illustrative purposes; they were used one at a time. The power meter was used to determine how much the beam circularization system attenuated the intensity of the input laser beam. The wavefront sensor provided a way to measure the aberrations of the output beam. The M^2 system measurement describes the resemblance of the output beam to a Gaussian beam. Ideally, the circularization systems would not attenuate or aberrate the laser beam, and they would output a perfectly Gaussian beam.





Edge-emitting laser diodes also emit astigmatic beams, and it can be desirable to force the displaced focal points of the orthogonal beam components to overlap. Of the three circularization techniques investigated in this work, only the cylindrical lens pair can also compensate for astigmatism. The displacement between the focal spots of the orthogonal beam components were measured for each circularization technique. In the case of the cylindrical lens pair, their configuration was tuned to minimize the astigmatism in the laser beam. The astigmatism was reported as a normalized quantity.

Experimental Results

The experimental results are summarized in the following table, in which the green cells identify the best result in each category. Each circularization approach has its benefits. The best circularization technique for an application is determined by the system's requirements for beam quality, transmitted optical power, and setup constraints.

Spatial filtering significantly improved the circularity and quality of the beam, but the beam had low transmitted power. The cylindrical lens pair provided a well-circularized beam and balanced circularization and beam quality with transmitted power. In addition, the cylindrical lens pair compensated for much of the beam's astigmatism. The circularity of the beam provided by the anamorphic prism pair compared well to that of the cylindrical lens pair. The beam output from the prisms had better M^2 values and less wavefront error than the cylindrical lenses, but the transmitted power was lower.

Method	Beam Intensity Profile	Circularity ^a	M^2 Values	RMS Wavefront	Transmitted Power	Normalized Astigmatism ^b
--------	------------------------	--------------------------	--------------	---------------	-------------------	-------------------------------------

Method	Beam Intensity Profile	Circularity ^a	M ² Values	RMS Wavefront	Transmitted Power	Normalized Astigmatism ^b
Collimated Source Output (No Circularization Technique)	 Click to Enlarge Scale in Microns	0.36	X Axis: 1.28 Y Axis: 1.63	0.17	Not Applicable	0.67
Cylindrical Lens Pair	 Click to Enlarge Scale in Microns	0.84	X Axis: 1.90 Y Axis: 1.93	0.30	91%	0.06
Anamorphic Prism Pair	 Click to Enlarge Scale in Microns	0.82	X Axis: 1.60 Y Axis: 1.46	0.16	80%	1.25
Spatial Filter	 Click to Enlarge Scale in Microns	0.93	X Axis: 1.05 Y Axis: 1.10	0.10	34%	0.36

- a. $Circularity = d_{minor} / d_{major}$, where d_{minor} and d_{major} are minor and major diameters of fitted ellipse (1/e intensity) and $Circularity = 1$ indicates a perfectly circular beam.
- b. Normalized astigmatism is the difference in the waist positions of the two orthogonal components of the beam, divided by the Raleigh length of the beam component with the smaller waist.

Components used in each circularization system were chosen to allow the same experimental setup be used for all experiments. This had the desired effect of allowing the results of all circularization techniques to be directly compared; however, optimizing the setup for a circularization technique could have improved its performance. The mounts used for the collimating lens and the anamorphic prism pair enabled easy manipulation and integration into this experimental system. It is possible that using smaller mounts would improve results by allowing the members of each pair to be more precisely positioned with respect to one another. In addition, using made-to-order cylindrical lenses with customized focal lengths may have improved the results of the cylindrical lens pair circularization system. All results may have been affected by the use of the beam profiler software algorithm to determine the beam radii used in the circularity calculation.

Additional Information

Some information describing selection and configuration procedures for several components used in this experimental work can be accessed by clicking the following hyperlinks:

- Mounting Laser Diodes
- Driving a Laser Diode
- Selecting a Collimating Lens
- Aspheric Lenses
- Spatial Filters

CAGE OVERVIEW

Cage System Overview


The Cage Assembly System provides a convenient way to construct large optomechanical systems with an established line of precision-machined building blocks designed for high flexibility and accurate alignment.

16 mm, 30 mm, and 60 mm Cage System Standards

Thorlabs offers three standards defined by the center-to-center spacing of the cage assembly rods (see image below). The 16 mm cage, 30 mm cage, and 60 mm cage standards are designed to accommodate Ø1/2", Ø1", and Ø2" optics, respectively. Specialized cage plates that allow smaller optics to be directly inserted into our larger cage systems are also available.

Standard Threads

The flexibility of our Cage Assembly System stems from well-defined mounting and thread standards designed to directly interface with a wide range of specialized products. The three most prevalent thread standards are our SM05 Series (0.535"-40 thread), SM1 Series (1.035"-40 thread), and SM2 Series (2.035"-40 thread), all of which were defined to house the industry's most common optic sizes. Essential building blocks, such as our popular lens tubes, directly interface to these standards.



An example of the standard cage plate measurements determining cage system compatibility.

Standard Cage System Measurements			
Cage System	16 mm	30 mm	60 mm
Thread Series	SM05	SM1	SM2
Rod to Rod Spacing	16 mm (0.63")	30 mm (1.18")	60 mm (2.36")
Total Length	25 mm (0.98")	41 mm (1.60")	71.1 mm (2.8")

Cage Components		
Cage Rods	16 mm	These rods are used to connect cage plates, optic mounts, and other components in the cage system. The SR Series Cage Rods are compatible with our 16 mm cage systems, while the 30 mm and 60 mm cage systems use ER Series Cage Rods.
	30 mm	
	60 mm	
Cage Plates	16 mm	These serve as the basic building blocks for a cage system. They may have SM-threaded central bores, smooth bores sized for industry standard optics or to accommodate the outer profile of our SM Series Lens Tubes, or specialized bores for other components such as our FiberPorts.
	30 mm	
	60 mm	
Optic Mounts	16 mm	Thorlabs offers fixed, kinematic, rotation, and translation mounts specifically designed for our Cage Systems.
	30 mm	
	60 mm	
Cage Cubes	16 mm	These cubes are useful for housing larger optical components, such as prisms or mirrors, or optics that need to sit at an angle to the beam path, such as beamsplitters. Our cage cubes are available empty or with pre-mounted optics.
	30 mm	
	60 mm	
Post and Breadboard Mounts and Adapters	Mounting options for cage systems can be found on our Cage System Construction pages. Cage Systems can be mounted either parallel or perpendicular to the table surface.	
Size Adapters	Cage System Size Adapters can be used to integrate components from different cage system and threading standards.	
Specialized Components	Thorlabs also produces specialized cage components, such as Filter Wheels, a HeNe Laser Mount, and a FiberPort Cage Plate Adapter, allowing a wide range of our products to be integrated into cage-mounted optical systems. Explore our Cage Systems Visual Navigation Guide to see the full range of Thorlabs' cage components.	

Free-Space to Fiber Coupler



- ▶ Accepts FC or SMA Fiber Cables
- ▶ Accepts Microscope Objectives
- ▶ High-Precision Differential Adjusters Provide Submicron Translation
- ▶ Easy-to-Follow Instructions and Alignment Tools

The KT120 and KT110/M fiber launch systems are designed to couple free-space laser beams into fiber optic cables terminated with either FC or SMA connectors. These fiber launch systems are directly compatible with many of our diffraction-limited aspheres, which offer superior performance when compared to traditional microscope objectives. The C230TMD aspheric lens, which has an equivalent microscope magnification of 35X, is an ideal choice for most free-space coupling applications.

Note: The individual optomechanical parts used in the KT120 assembly are imperial or universal, while the parts used in the KT110/M assembly are metric or universal.

Part Number	Description	Price	Availability
KT110/M	Fiber Launch System: Free Space, Metric (Coupling Optic Sold Separately)	\$1,184.92	Lead Time
KT120	NEW! Fiber Launch System: Free Space (Coupling Optic Sold Separately)	\$1,184.92	Lead Time

Spatial Filter System



- ▶ Produces a Clean Gaussian Beam
- ▶ Wide Assortment of Compatible Pinholes, Aspheric Lenses, and Collimating Lenses
- ▶ Pre-Assembled System of Stock Catalog Components

The KT311(/M) spatial filter is ideal for producing a "clean" Gaussian beam. The input side consists of a Z-translator that will hold a diffraction-limited aspheric lens to focus the laser through a pinhole. For easy adjustment, the pinhole should be mounted in the XY translator. Threaded holes on the output side are provided for mounting and centering a Ø1" collimating optic. Please see the *Tutorial* tab for more information on selecting the appropriate optics and pinhole for your application.

Note: The individual optomechanical parts used in the KT311 assembly are imperial or universal while the parts used in the KT311/M assembly are metric or universal.

Part Number	Description	Price	Availability
KT311/M	NEW! Spatial Filter System, Metric (Optics & Pinhole Sold Separately)	\$970.66	Lead Time
KT311	NEW! Spatial Filter System (Optics & Pinhole Sold Separately)	\$970.66	Today