

NENIR03A - September 9, 2022

Item # NENIR03A was discontinued on September 9, 2022. For informational purposes, this is a copy of the website content at that time and is valid only for the stated product.

MOUNTED NIR ABSORPTIVE ND FILTERS

- ▶ Optimized for Attenuation at 1064 nm and 1550 nm
- ▶ Ø25 mm Mounted Filters in SM1-Threaded Mounts
- ▶ Transmission at Visible Wavelengths for Beam Alignment
- ▶ Effective Heat Absorbing Filters



NENIR03A




NENIR13A

[Hide Overview](#)

OVERVIEW

Features

- Ø25 mm Filters in Mounts with Internal and External SM1 (1.035"-40) Threads
- Design Wavelength: 1550 nm
- Optical Densities Ranging from 0.1 to 6.0
- Ideal for Low-Power Applications (<1 W; see the *Specs* Tab for Additional Details)
- Effective Attenuators from 1000 to 2600 nm
- Good Visible Wavelength Transmission (See Graph to the Right)
- Absorptive Glass Reduces Multiple Reflections



Click to Enlarge

These Ø25 mm infrared absorptive neutral density filters in SM1-threaded mounts have optical densities ranging from 0.1 to 6.0. These shortpass, heat-protective filters are transmissive in the visible region, allowing for passage of an alignment beam, and absorptive in the near infrared. Although optimized at 1550 nm, this optimization also leads to excellent performance at 1064 nm (see below for more details). These filters have a relatively flat spectral response from 1000 - 1600 nm and are effective attenuators up to 2600 nm. They can also be used as heat absorbing filters, transmitting <2% above 4 µm.

The mounts feature internal and external SM1 (1.035"-40) threading. If desired, a mounted filter can be removed from its housing by unscrewing the retaining ring that secures the filter to the mount. Thorlabs offers a range of spanner wrenches that are an ideal match to these retaining rings. The filters on this page are also available unmounted. The equivalent unmounted filter is listed in the drawing for each mounted filter, accessible through the red docs icons (📄) below.

Neutral Density Filter Selection Guide

Absorptive

Uncoated (400 - 650 nm)	Mounted Unmounted
Uncoated (1000 - 2600 nm)	Mounted Unmounted
AR Coated (350 - 700 nm)	Mounted Unmounted
AR Coated (650 - 1050 nm)	Mounted Unmounted
AR Coated (1050 - 1700 nm)	Mounted Unmounted

Variable

Reflective

UV Fused Silica (200 - 1200 nm)	Mounted Unmounted
	Mounted

Each absorptive NIR ND filter is fabricated from one member of a family of Schott glasses (NG11, KG2, KG3, or KG5). Each Schott glass has a spectrally flat absorption coefficient from 1000 - 1600 nm. By varying the thickness of the glass, we are able to produce our entire line of NIR ND filters from just four types of Schott glass. Refer to the *Graphs* tab above for detailed information about the average transmission obtained with each of our absorptive neutral density filters. For applications that would benefit from reduced surface reflections, Thorlabs offers NIR absorptive ND filters with an AR coating for the 1050 - 1700 nm wavelength range.

The filters sold on this page are uncoated. For our full selection of coated and uncoated ND filters, please see the Selection Guide table on the right.

Optical Density and Transmission

Optical density (OD) indicates the attenuation factor provided by an optical filter, i.e. how much it reduces the optical power of an incident beam. OD is related to the transmission, T, by the equation

$$OD = \log_{10} \left(\frac{1}{T} \right), \text{ or } T = 10^{-OD}$$

where T is a value between 0 and 1. Choosing an ND filter with a higher optical density will translate to lower transmission and greater absorption of the incident light. For higher transmission and less absorption, a lower optical density would be appropriate. As an example, if a filter with an OD of 2 results in a transmission value of 0.01, this means the filter attenuates the beam to 1% of the incident power. Please note that the transmission data for our neutral density filters is provided in percent (%).

Please note that these products are not designed for use as laser safety equipment. For lab safety, Thorlabs offers an extensive line of safety and blackout products, including beam blocks, that significantly reduce exposure to stray light.

N-BK7 (350 - 1100 nm)	
	Unmounted
ZnSe (2 - 16 μm)	Mounted
	Unmounted
Wedged UVFS (200 - 1200 nm)	
Wedged N-BK7 (350 - 1100 nm)	
Wedged ZnSe (2 - 16 μm)	
Variable	
Neutral Density Filter Kits	



[Hide Specs](#)

S P E C S

General Specifications	
Housing Outer Diameter	1.20"
Optic Diameter	25.0 mm
Optic Diameter Tolerance	+0.0 / -0.2 mm
Clear Aperture	90% of Optic Diameter (for 0.5, 1.0, 2.0, 3.0, and 4.0 ODs) >90% of Optic Diameter (for All Other ODs)
Surface Flatness	<λ/4 @ 633 nm (for 0.7, 0.8, 0.9, and 1.5 ODs) λ/4 @ 633 nm (for All Other ODs)
Design Wavelength	1550 nm
Wavelength Range	1000 - 2600 nm
Surface Quality	40-20 Scratch-Dig
Parallelism	<10 arcsec
Optical Density Tolerance	±5% @ 1550 nm


Damage Threshold Specifications		
Optical Density	Damage Threshold	
1.0	Pulsed	8 J/cm ² (1064 nm, 10 ns, 10 Hz, Ø1.040 mm) 20 J/cm ² (1542 nm, 10 ns, 10 Hz, Ø0.144 mm)
	CW ^{a,b}	25 W/cm (1540 nm, Ø1.030 mm)
3.0	CW ^{a,b}	25 W/cm (1064 nm, Ø0.062 mm)
5.0	CW ^{a,b}	15 W/cm (1540 nm, Ø1.030 mm)

a. The power density of your beam should be calculated in terms of W/cm.


For an explanation of why the linear power density provides the best metric for long pulse and CW sources, please see the *Damage Thresholds* tab.
b. CW testing was performed using a 30 second exposure at each test site.

[Hide Graphs](#)

GRAPHS



[Click to Enlarge](#)



[Click to Enlarge](#)

[Click here to download optical density and transmission data.](#)

For the transmission and optical density of a particular filter, please click [i](#) in the row corresponding to the filter in the table below.

[Hide Damage Thresholds](#)

DAMAGE THRESHOLDS

Damage Threshold Data for Thorlabs' NIR Absorptive ND Filters

The specifications to the right are measured data for Thorlabs' NIR absorptive ND filters. Damage threshold specifications are constant for a given optical density, regardless of the size of the filter. CW testing for these filters was performed using a 30 second exposure at each test site.

Damage Threshold Specifications		
Optical Density	Damage Threshold	
1.0	Pulsed	8 J/cm ² (1064 nm, 10 ns, 10 Hz, Ø1.040 mm) 20 J/cm ² (1542 nm, 10 ns, 10 Hz, Ø0.144 mm)
	CW ^{a,b}	25 W/cm (1540 nm, Ø1.030 mm)
3.0	CW ^{a,b}	25 W/cm (1064 nm, Ø0.062 mm)
5.0	CW ^{a,b}	15 W/cm (1540 nm, Ø1.030 mm)

- a. The power density of your beam should be calculated in terms of W/cm.
For an explanation of why the linear power density provides the best metric for long pulse and CW sources, please see the "Continuous Wave and Long-Pulse Lasers" section below.
- b. CW testing was performed using a 30 second exposure at each test site.

Laser Induced Damage Threshold Tutorial

The following is a general overview of how laser induced damage thresholds are measured and how the values may be utilized in determining the appropriateness of an optic for a given application. When choosing optics, it is important to understand the Laser Induced Damage Threshold (LIDT) of the optics being used. The LIDT for an optic greatly depends on the type of laser you are using. Continuous wave (CW) lasers typically cause damage from thermal effects (absorption either in the coating or in the substrate). Pulsed lasers, on the other hand, often strip electrons from the lattice structure of an optic before causing thermal damage. Note that the guideline presented here assumes room temperature operation and optics in new condition (i.e., within scratch-dig spec, surface free of contamination, etc.). Because dust or other particles on the surface of an optic can cause damage at lower thresholds, we recommend keeping surfaces clean and free of debris. For more information on cleaning optics, please see our *Optics Cleaning* tutorial.

Testing Method

Thorlabs' LIDT testing is done in compliance with ISO/DIS 11254 and ISO 21254 specifications.

First, a low-power/energy beam is directed to the optic under test. The optic is exposed in 10 locations to this laser beam for 30 seconds (CW) or for a number of pulses (pulse repetition frequency specified). After exposure, the optic is examined by a microscope (~100X magnification) for any visible damage. The number of locations that are damaged at a particular power/energy level is recorded. Next, the power/energy is either increased or decreased and the optic is exposed at 10 new locations. This process is repeated until damage is observed. The damage threshold is then assigned to be the highest power/energy that the optic can withstand without causing damage. A histogram such as that below represents the testing of one BB1-E02 mirror.



The photograph above is a protected aluminum-coated mirror after LIDT testing. In this particular test, it handled 0.43 J/cm² (1064 nm, 10 ns pulse, 10 Hz, Ø1.000 mm) before damage.

According to the test, the damage threshold of the mirror was 2.00 J/cm² (532 nm, 10 ns pulse, 10 Hz, Ø0.803 mm). Please keep in mind that these tests are performed on clean optics, as dirt and contamination can significantly lower the damage threshold of a component. While the test results are only representative of one coating run, Thorlabs specifies damage threshold values that account for coating variances.

Continuous Wave and Long-Pulse Lasers

When an optic is damaged by a continuous wave (CW) laser, it is usually due to the melting of the surface as a result of absorbing the laser's energy or damage to the optical coating (antireflection) [1]. Pulsed lasers with pulse lengths longer than 1 µs can be treated as CW lasers for LIDT discussions.


When pulse lengths are between 1 ns and 1 µs, laser-induced damage can occur either because of absorption or a dielectric breakdown (therefore, a user must check both CW and pulsed LIDT). Absorption is either due to an intrinsic property of the optic or due to surface irregularities; thus LIDT values are only valid for optics meeting or exceeding the surface quality specifications given by a manufacturer. While many optics can handle high power CW lasers, cemented (e.g., achromatic doublets) or highly absorptive (e.g., ND filters) optics tend to have lower CW damage thresholds. These lower thresholds are due to absorption or scattering in the cement or metal coating.

Pulsed lasers with high pulse repetition frequencies (PRF) may behave similarly to CW beams. Unfortunately, this is highly dependent on factors such as absorption and thermal diffusivity, so there is no reliable method for determining when a high PRF laser will damage an optic due to thermal effects. For beams with a high PRF both the average and peak powers must be compared to the equivalent CW power. Additionally, for highly transparent materials, there is little to no drop in the LIDT with increasing PRF.


In order to use the specified CW damage threshold of an optic, it is necessary to know the following:

1. Wavelength of your laser
2. Beam diameter of your beam (1/e²)
3. Approximate intensity profile of your beam (e.g., Gaussian)
4. Linear power density of your beam (total power divided by 1/e² beam diameter)

Thorlabs expresses LIDT for CW lasers as a linear power density measured in W/cm. In this regime, the LIDT given as a linear power density can be applied to any beam diameter; one does not need to compute an adjusted LIDT to adjust for changes in spot size, as demonstrated by the graph to the right. Average linear power density can be calculated using the equation below.




Example Test Data			
Fluence	# of Tested Locations	Locations with Damage	Locations Without Damage
1.50 J/cm ²	10	0	10
1.75 J/cm ²	10	0	10
2.00 J/cm ²	10	0	10
2.25 J/cm ²	10	1	9
3.00 J/cm ²	10	1	9
5.00 J/cm ²	10	9	1



LIDT in linear power density vs. pulse length and spot size. For long pulses to CW, linear power density becomes a constant with spot size. This graph was obtained from [1].

Linear Power Density = $\frac{\text{Power}}{\text{Beam Diameter}}$



The calculation above assumes a uniform beam intensity profile. You must now consider hotspots in the beam or other non-uniform intensity profiles and roughly calculate a maximum power density. For reference, a Gaussian beam typically has a maximum power density that is twice that of the uniform beam (see lower right).

Now compare the maximum power density to that which is specified as the LIDT for the optic. If the optic was tested at a wavelength other than your operating wavelength, the damage threshold must be scaled appropriately. A good rule of thumb is that the damage threshold has a linear relationship with wavelength such that as you move to shorter wavelengths, the damage threshold decreases (i.e., a LIDT of 10 W/cm at 1310 nm scales to 5 W/cm at 655 nm):

Adjusted LIDT = *LIDT Power* $\left(\frac{\text{Your Wavelength}}{\text{LIDT Wavelength}} \right)$

While this rule of thumb provides a general trend, it is not a quantitative analysis of LIDT vs wavelength. In CW applications, for instance, damage scales more strongly with absorption in the coating and substrate, which does not necessarily scale well with wavelength. While the above procedure provides a good rule of thumb for LIDT values, please contact Tech Support if your wavelength is different from the specified LIDT wavelength. If your power density is less than the adjusted LIDT of the optic, then the optic should work for your application.

Please note that we have a buffer built in between the specified damage thresholds online and the tests which we have done, which accommodates variation between batches. Upon request, we can provide individual test information and a testing certificate. The damage analysis will be carried out on a similar optic (customer's optic will not be damaged). Testing may result in additional costs or lead times. Contact Tech Support for more information.

Pulsed Lasers

As previously stated, pulsed lasers typically induce a different type of damage to the optic than CW lasers. Pulsed lasers often do not heat the optic enough to damage it; instead, pulsed lasers produce strong electric fields capable of inducing dielectric breakdown in the material. Unfortunately, it can be very difficult to compare the LIDT specification of an optic to your laser. There are multiple regimes in which a pulsed laser can damage an optic and this is based on the laser's pulse length. The highlighted columns in the table below outline the relevant pulse lengths for our specified LIDT values.

Pulses shorter than 10⁻⁹ s cannot be compared to our specified LIDT values with much reliability. In this ultra-short-pulse regime various mechanics, such as multiphoton-avalanche ionization, take over as the predominate damage mechanism [2]. In contrast, pulses between 10⁻⁷ s and 10⁻⁴ s may cause damage to an optic either because of dielectric breakdown or thermal effects. This means that both CW and pulsed damage thresholds must be compared to the laser beam to determine whether the optic is suitable for your application.

Pulse Duration	t < 10 ⁻⁹ s	10 ⁻⁹ < t < 10 ⁻⁷ s	10 ⁻⁷ < t < 10 ⁻⁴ s	t > 10 ⁻⁴ s
Damage Mechanism	Avalanche Ionization	Dielectric Breakdown	Dielectric Breakdown or Thermal	Thermal
Relevant Damage Specification	No Comparison (See Above)	Pulsed	Pulsed and CW	CW

When comparing an LIDT specified for a pulsed laser to your laser, it is essential to know the following:

- 1. Wavelength of your laser
- 2. Energy density of your beam (total energy divided by 1/e² area)
- 3. Pulse length of your laser
- 4. Pulse repetition frequency (prf) of your laser
- 5. Beam diameter of your laser (1/e²)
- 6. Approximate intensity profile of your beam (e.g., Gaussian)

The energy density of your beam should be calculated in terms of J/cm². The graph to the right shows why expressing the LIDT as an energy density provides the best metric for short pulse sources. In this regime, the LIDT given as an energy density

can be applied to any beam diameter; one does not need to compute an adjusted LIDT to adjust for changes in spot size. This calculation assumes a uniform beam intensity profile. You must now adjust this energy density to account for hotspots or other nonuniform intensity profiles and roughly calculate a maximum energy density. For reference a Gaussian beam typically has a maximum energy density that is twice that of the $1/e^2$ beam.

Now compare the maximum energy density to that which is specified as the LIDT for the optic. If the optic was tested at a wavelength other than your operating wavelength, the damage threshold must be scaled appropriately [3]. A good rule of thumb is that the damage threshold has an inverse square root relationship with wavelength such that as you move to shorter wavelengths, the damage threshold decreases (i.e., a LIDT of 1 J/cm² at 1064 nm scales to 0.7 J/cm² at 532 nm):

$$\text{Adjusted LIDT} = \text{LIDT Energy} \sqrt{\frac{\text{Your Wavelength}}{\text{LIDT Wavelength}}}$$

You now have a wavelength-adjusted energy density, which you will use in the following step.

Beam diameter is also important to know when comparing damage thresholds. While the LIDT, when expressed in units of J/cm², scales independently of spot size; large beam sizes are more likely to illuminate a larger number of defects which can lead to greater variances in the LIDT [4]. For data presented here, a <1 mm beam size was used to measure the LIDT. For beams sizes greater than 5 mm, the LIDT (J/cm²) will not scale independently of beam diameter due to the larger size beam exposing more defects.


The pulse length must now be compensated for. The longer the pulse duration, the more energy the optic can handle. For pulse widths between 1 - 100 ns, an approximation is as follows:

$$\text{Adjusted LIDT} = \text{LIDT Energy} \sqrt{\frac{\text{Your Pulse Length}}{\text{LIDT Pulse Length}}}$$

Use this formula to calculate the Adjusted LIDT for an optic based on your pulse length. If your maximum energy density is less than this adjusted LIDT maximum energy density, then the optic should be suitable for your application. Keep in mind that this calculation is only used for pulses between 10⁻⁹ s and 10⁻⁷ s. For pulses between 10⁻⁷ s and 10⁻⁴ s, the CW LIDT must also be checked before deeming the optic appropriate for your application.

Please note that we have a buffer built in between the specified damage thresholds online and the tests which we have done, which accommodates variation between batches. Upon request, we can provide individual test information and a testing certificate. Contact Tech Support for more information.

[1] R. M. Wood, Optics and Laser Tech. **29**, 517 (1998).
[2] Roger M. Wood, *Laser-Induced Damage of Optical Materials* (Institute of Physics Publishing, Philadelphia, PA, 2003).
[3] C. W. Carr *et al.*, Phys. Rev. Lett. **91**, 127402 (2003).
[4] N. Bloembergen, Appl. Opt. **12**, 661 (1973).



LIDT in energy density vs. pulse length and spot size. For short pulses, energy density becomes a constant with spot size. This graph was obtained from [1].

[Hide LIDT Calculations](#)

LIDT CALCULATIONS

In order to illustrate the process of determining whether a given laser system will damage an optic, a number of


example calculations of laser induced damage threshold are given below. For assistance with performing similar calculations, we provide a spreadsheet calculator that can be downloaded by clicking the button to the right. To use the calculator, enter the specified LIDT value of the optic under consideration and the relevant parameters of your laser system in the green boxes. The spreadsheet will then calculate a linear power density for CW and pulsed systems, as well as an energy density value for pulsed systems. These values are used to calculate adjusted, scaled LIDT values for the optics based on accepted scaling laws. This calculator assumes a Gaussian beam profile, so a correction factor must be introduced for other beam shapes (uniform, etc.). The LIDT scaling laws are determined from empirical relationships; their accuracy is not guaranteed. Remember that absorption by optics or coatings can significantly reduce LIDT in some spectral regions. These LIDT values are not valid for ultrashort pulses less than one nanosecond in duration.

CW Laser Example

Suppose that a CW laser system at 1319 nm produces a 0.5 W Gaussian beam that has a 1/e² diameter of 10 mm. A naive calculation of the average linear power density of this beam would yield a value of 0.5 W/cm, given by the total power divided by the beam diameter:

$$\text{Linear Power Density} = \frac{\text{Power}}{\text{Beam Diameter}}$$

However, the maximum power density of a Gaussian beam is about twice the maximum power density of a uniform beam, as shown in the graph to the right. Therefore, a more accurate determination of the maximum linear power density of the system is 1 W/cm.



A Gaussian beam profile has about twice the maximum intensity of a uniform beam profile.

An AC127-030-C achromatic doublet lens has a specified CW LIDT of 350 W/cm, as tested at 1550 nm. CW damage threshold values typically scale directly with the wavelength of the laser source, so this yields an adjusted LIDT value:

$$\text{Adjusted LIDT} = \text{LIDT Power} \left(\frac{\text{Your Wavelength}}{\text{LIDT Wavelength}} \right)$$

The adjusted LIDT value of 350 W/cm x (1319 nm / 1550 nm) = 298 W/cm is significantly higher than the calculated maximum linear power density of the laser system, so it would be safe to use this doublet lens for this application.

Pulsed Nanosecond Laser Example: Scaling for Different Pulse Durations

Suppose that a pulsed Nd:YAG laser system is frequency tripled to produce a 10 Hz output, consisting of 2 ns output pulses at 355 nm, each with 1 J of energy, in a Gaussian beam with a 1.9 cm beam diameter (1/e²). The average energy density of each pulse is found by dividing the pulse energy by the beam area:

$$\text{Energy Density} = \frac{\text{Pulse Energy}}{\text{Beam Area}}$$

As described above, the maximum energy density of a Gaussian beam is about twice the average energy density. So, the maximum energy density of this beam is ~0.7 J/cm².

The energy density of the beam can be compared to the LIDT values of 1 J/cm² and 3.5 J/cm² for a BB1-E01 broadband dielectric mirror and an NB1-K08 Nd:YAG laser line mirror, respectively. Both of these LIDT values, while measured at 355 nm, were determined with a 10 ns pulsed laser at 10 Hz. Therefore, an adjustment must be applied for the shorter pulse duration of the system under consideration. As described on the previous tab, LIDT values in the nanosecond pulse regime scale with the square root of the laser pulse duration:

$$\text{Adjusted LIDT} = \text{LIDT Energy} \sqrt{\frac{\text{Your Pulse Length}}{\text{LIDT Pulse Length}}}$$

This adjustment factor results in LIDT values of 0.45 J/cm² for the BB1-E01 broadband mirror and 1.6 J/cm² for the Nd:YAG laser line mirror, which are to be compared with the 0.7 J/cm² maximum energy density of the beam. While the broadband mirror would likely be damaged by the laser, the more specialized laser line mirror is appropriate for use with this system.

Pulsed Nanosecond Laser Example: Scaling for Different Wavelengths

Suppose that a pulsed laser system emits 10 ns pulses at 2.5 Hz, each with 100 mJ of energy at 1064 nm in a 16 mm diameter beam (1/e²) that must be attenuated with a neutral density filter. For a Gaussian output, these specifications result in a maximum energy density of 0.1 J/cm². The damage threshold of an NDUV10A Ø25 mm, OD 1.0, reflective neutral density filter is 0.05 J/cm² for 10 ns pulses at 355 nm, while the damage threshold of the similar NE10A absorptive filter is 10 J/cm² for 10 ns pulses at 532 nm. As described on the previous tab, the LIDT value of an optic scales with the square root of the wavelength in the nanosecond pulse regime:

Adjusted LIDT = LIDT Energy
$$\sqrt{\frac{\text{Your Wavelength}}{\text{LIDT Wavelength}}}$$

This scaling gives adjusted LIDT values of 0.08 J/cm² for the reflective filter and 14 J/cm² for the absorptive filter. In this case, the absorptive filter is the best choice in order to avoid optical damage.


















Pulsed Microsecond Laser Example


Consider a laser system that produces 1 µs pulses, each containing 150 µJ of energy at a repetition rate of 50 kHz, resulting in a relatively high duty cycle of 5%. This system falls somewhere between the regimes of CW and pulsed laser induced damage, and could potentially damage an optic by mechanisms associated with either regime. As a result, both CW and pulsed LIDT values must be compared to the properties of the laser system to ensure safe operation.

If this relatively long-pulse laser emits a Gaussian 12.7 mm diameter beam (1/e²) at 980 nm, then the resulting output has a linear power density of 5.9 W/cm and an energy density of 1.2 x 10⁻⁴ J/cm² per pulse. This can be compared to the LIDT values for a WPQ10E-980 polymer zero-order quarter-wave plate, which are 5 W/cm for CW radiation at 810 nm and 5 J/cm² for a 10 ns pulse at 810 nm. As before, the CW LIDT of the optic scales linearly with the laser wavelength, resulting in an adjusted CW value of 6 W/cm at 980 nm. On the other hand, the pulsed LIDT scales with the square root of the laser wavelength and the square root of the pulse duration, resulting in an adjusted value of 55 J/cm² for a 1 µs pulse at 980 nm. The pulsed LIDT of the optic is significantly greater than the energy density of the laser pulse, so individual pulses will not damage the wave plate. However, the large average linear power density of the laser system may cause thermal damage to the optic, much like a high-power CW beam.

[Hide Ø25 mm Mounted NIR ND Filters](#)

Ø25 mm Mounted NIR ND Filters

Item #	Substrate (Schott)	Substrate Thickness ^a	Optical Density at 1064 nm ^{b,c}	Transmission at 1064 nm ^{b,c}	Optical Density at 1550 nm ^b	Transmission at 1550 nm ^b	Transmission Data ^d
NENIR01A	NG11	0.5 mm	0.14	72.44%	0.09 ^e	81.28%	
NENIR02A	NG11	1.2 mm	0.28	52.49%	0.16 ^e	69.18%	
NENIR03A	KG2	0.5 mm	0.32	47.79%	0.29 ^e	50.62%	
NENIR04A	KG2	0.6 mm	0.43	37.84%	0.39 ^e	40.93%	
NENIR05A	KG2	0.8 mm	0.53	29.21%	0.49 ^e	32.26%	
NENIR06A	KG2	1.0 mm	0.65	23.61%	0.58 ^e	29.59%	
NENIR07A	KG2	1.1 mm	0.74	18.20%	0.68 ^f	20.89%	
NENIR08A	KG2	1.3 mm	0.85	14.13%	0.77 ^f	16.98%	
NENIR09A	KG2	1.4 mm	0.96	10.96%	0.86 ^f	13.80%	
NENIR10A	KG2	1.6 mm	1.07	8.57%	0.98 ^e	10.51%	
NENIR13A	KG3	0.8 mm	1.41	3.81%	1.27 ^e	5.18%	
NENIR15A	KG3	1.0 mm	1.61	2.45%	1.44 ^f	3.63%	
NENIR20A	KG3	1.3 mm	2.14	0.73%	1.95 ^e	1.12%	
NENIR30A	KG3	2.0 mm	3.18	0.07%	2.88 ^e	0.13%	
NENIR40A	KG3	2.6 mm	4.13	0.01%	3.81 ^e	0.02%	
NENIR50A	HA5	2.3 mm	5.29	0.0005%	4.74 ^e	0.002%	
NENIR60A	HA5	2.8 mm	6.38	0.00004%	5.71 ^e	0.0002%	

- a. Values given are typical.
- b. The actual thickness of each ND filter is dependent on the optical density of the lot of glass used to manufacture each lot of ND filters. Optical density values are not exactly 0.5, 1.0, etc., at 1064 nm or 1550 nm in order to provide good performance at both wavelengths.
- c. Values are typical.
- d. Click on  for a plot and downloadable data.
- e. Tolerance of <5%
- f. Tolerance of ±5%

Part Number	Description	Price	Availability
NENIR01A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 0.1	\$67.00	Today
NENIR02A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 0.2	\$67.00	Today
NENIR03A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 0.3	\$67.00	7-10 Days
NENIR04A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 0.4	\$67.00	7-10 Days
NENIR05A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 0.5	\$67.00	Today
NENIR06A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 0.6	\$67.00	Today
NENIR07A	Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 0.7	\$67.00	Today
NENIR08A	Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 0.8	\$67.00	Today
NENIR09A	Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 0.9	\$67.00	Today
NENIR10A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 1.0	\$67.00	Today
NENIR13A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 1.3	\$67.00	Today
NENIR15A	Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 1.5	\$67.00	Today
NENIR20A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 2.0	\$67.00	Today
NENIR30A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 3.0	\$67.00	Today
NENIR40A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 4.0	\$67.00	Today
NENIR50A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 5.0	\$67.00	Lead Time
NENIR60A	Customer Inspired! Ø25 mm NIR Absorptive ND Filter, SM1-Threaded Mount, OD: 6.0	\$67.00	Today

Graphs

The shaded regions in the graphs below denote the wavelength range over which we recommend using this filter, and the dotted line denotes the filter's nominal optical density. To view an excel file that lists all of the measured transmission values for this filter from 200 nm to 16 µm, please click [here](#).

